## KECES NEW LAUNCHES OF SUPERIOR SERIES S4 STEREO PREAMPLIFIER





The KECES has been striving to remove the ambient noise from audio, and to make you enjoy the pure and crystal-clear sound quality, just like live performance. The new stereo preamplifier S4 is the world's first preamplifier which build in DS Audio's equalizer.

This new launched of preamplifier with build in DS audio EQ and normal MC/MM phono will give many people a change to play Analog Turntable again at an affordable price.

The S4 preamplifier uses a single-ended, zero feedback circuit topology.

S4 is of fully symmetrical construction, and offers a wide range of symmetrical (XLR) and asymmetrical (RCA) inputs and corresponding outputs.

Equipped with a high-quality headphone amplifier and is supplied complete with the all-metal infrared remote control handset.

DS Audio has been one of the pioneers in the industry for cartridge production, and we are honored to have collaborated with them. This partnership allows us to offer more choices of equalization solutions for existing DS Audio customers.

## **KEY SPECIFICATIONS**



Input	MM/MC*1 / Optical*1 / RCA*1 / XLR*2
Input Impedance	MC: 56/100/220/470/47K
	MM: 47K
	OPT: more than 10K
	RCA/XLR:170K
Output	RCA*2 / XLR*1/ Headphone XLR-4pin
Total harmonic distortion (THD+N)	MM<0.02%, MC<0.05%, OPT<0.04%
	RCA<0.0015%, XLR<0.0015%
S/N R:	MM:78dB A-Weighted
	MC: 70dB A-weighted
	Optical: 75dB A-weighted
	RCA: 110db A-weighted
	XLR: 110dB A-weighted
Gain	MM:52dB / MC:72dB / Opt:32dB
	RCA/XLR: 20dB
Power Requirement	Standby: 0.5 Watt
	Maximum: 20 Watts
Casing	All Aluminum
Dimension (WxDxH)	300x279x66mm*2
Weight	Net Weight 4.5KG(Power) / 3.5KG(Pre)
	Shipping Weight 10KG